

## BALLAST COMPATIBLE PL LED INSTALLATION INSTRUCTIONS

These instructions apply to the PL LED models listed in the table below. Prior to installation, please read the entire installation instructions.

**DANGER** - Risk of Electric shock. Disconnect power to the luminaire at the source before installation.  
**WARNING** - Risk of Fire or electric shock. LED Retrofit Kit installation requires knowledge of luminaires electrical systems. If not qualified, do not attempt installation. Contact a qualified electrician. Installation should be performed by a qualified electrician in accordance with the National Electrical Code and relevant local code.

**WARNING** - Risk of fire or electrical shock. Install this kit only in the luminaires that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating does not exceed the input rating of the luminaire.

**WARNING** - To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.

**CAUTION** - If the lamp or luminaire exhibits undesirable operation, immediately turn off the power, remove the lamp and contact the manufacturer.

**This device is not intended for use with Emergency Exits**

Suitable for use in damp locations. Do not use where exposed to water.  
 Suitable for use with compatible electronic ballast. Please see list below.  
 Suitable for use in open, semi-enclosed or recessed fixtures.



## INSTALLATION REQUIREMENTS

Model	Voltage	Ballast Compatibility	Base Type	Environment	Acceptable Fixtures	Minimum Compartment Dims.	
LED-7330-XXK-G2	N/A	Compatible Electronic Ballast. See list below.	G24q and GX24q	Suitable for dry or damp locations	Indoor - Open Fixture Indoor - Recessed	3.5"	7.0"
LED-7334-XXK-G2							

### CONTENTS

1 pc LED Retrofit Lamp



1 pc Re-Lamping Label

1 pc Installation Instructions

### INSTALLATION INSTRUCTIONS

- Turn off power to the luminaire at switch and circuit breaker
- Allow luminaire to cool and remove lamps
- Ensure that the luminaire, ballast and electrical input meet the requirements listed above.
- Please confirm that it is a compatible ballast. The compatible ballast list only lists ballasts that were tested. Other ballasts may also work.
- Insert the lamp into the lamp holder.
- Apply the silver adhesive label to the inside of the luminaire where it will be visible during re-lamping.
- Turn on the power to the fixture and verify proper operation.

### WIRING DIAGRAM AND BALLAST COMPATIBILITY LIST



### Ballast Compatibility List

Brand	Model	Volt	1-Lamp		2-Lamp	
			120V	277V	120V	277V
GE	GEC218-MVPS-3W	120-277V	✓	✓	✓	✓
GE	GEC226-MVPS-3W	120-277V	✓	✓	✓	✓
PHILIPS/ADVANCE	ICF-2S18-H1-LD	120-277V	✓	✓	✓	✓
PHILIPS/ADVANCE	ICF-2S26-H1-LD	120-277V	✓	✓	✓	✓
PHILIPS/ADVANCE	ICF-2S42-M2-LD	120-277V	✓	✓	✓	✓
Universal/Triad	C218UNVSE	120-277V	✓	✓	✓	✓
Universal/Triad	C213UNVME	120-277V	✓	✓	✓	✓
Universal/Triad	C2642UNVME	120-277V	✓	✓	✓	✓
OSRAM	2*26CF/UNV DM(OSRAM)	120-277V	✓	✓	✓	✓
SYLVANIA	2*26CF/UNV DM(SYLVANIA)	120-277V	✗	✗	✗	✗
FULHAM	WH2-277-L	120-277V	✗	✓	✗	✗
HATCH	HC213PS/UV/D	120-277V	✗	✗	✗	✗
HATCH	HC218PS/UV/WJ	120-277V	✓	✓	✓	✓
HATCH	HC218PS/UV/D	120-277V	✗	✗	✗	✗
KEystone	KTEB-226-UV-PS-DW	120-277V	✗	✗	✗	✗
PONY	NPY-120-128CFL	120V	✗	✗	✗	✗
			✓	= compatible		
			✗	= not compatible		